



TOUGHBOOK FZ-T1

- Android™ 8.1 (Oreo)
- Integrated straight-shooting 1D/2D barcode reader with optional triggered pistol grip
- Industry standard quad-core processor by Qualcomm®
- Optional multi-carrier 4G LTE data support with cellular voice capability
- Loud speaker with noise suppression and echo cancellation microphones
- Designed to meet MIL-STD-810G, 5' Drop, All-weather IP66 and IP68 dust and water-resistant design
- 5" HD display with glove and rain mode
- 1 Year warranty with business class support

5-FOOT
DROP RATING

IP66

IP68

A SLEEK RUGGED HANDHELD FOR MISSION CRITICAL ENTERPRISE WORK WITH INTEGRATED BARCODE READER.

The Panasonic Toughbook® FZ-T1 is a slim and sleek Android OS based handheld that proudly carries the Toughbook name. Its ability to be used in the enterprise to collect information from workers in retail stores, warehouses field service, transportation and delivery or many other environments where work must occur belies its mild looking exterior. The FZ-T1 has a quad-core processor and a straight-shooting barcode reader, options to have a pistol grip with trigger, use a stylus pen or connect to multi-carrier 4G LTE with voice capability, yet end users will feel comfortable with its Android OS. This handheld's user's won't miss a beat with its great battery life, glove and rain touch enabled 5" screen, 5 foot drop rating and IP66 and IP68 certification. The Toughbook FZ-T1 is ready to be used by satisfied end users everywhere in your organization.

TOUGHBOOK FZ-T1

DURABILITY	<ul style="list-style-type: none"> Designed to meet MIL-STD-810G¹⁶ IP66 and IP68 sealed all-weather design 5' drop-resistant and tumble tested (500 tumbles, 3.3ft. 5 rpm)
SOFTWARE	<ul style="list-style-type: none"> Android 8.1 (Oreo)¹⁷
CPU	<ul style="list-style-type: none"> Qualcomm® MSM8909 1.1GHz Quad-Core
STORAGE & MEMORY	<ul style="list-style-type: none"> Memory 2GB¹ Storage eMMC: 16 GB¹ <ul style="list-style-type: none"> Additional storage available with optional Storage Card: <ul style="list-style-type: none"> SD (up to 2 GB), SDHC (up to 32 GB), SDXC (up to 64 GB)²
DISPLAY	<ul style="list-style-type: none"> 5" high definition 1280 x 720 10-point capacitive multi touch with rain sensing and glove touch modes <ul style="list-style-type: none"> Optional Passive Stylus Display with direct bonding Automatic screen rotation
AUDIO	<ul style="list-style-type: none"> Integrated microphone (x3) Loud volume speaker (mono) x 1 up to 95 db Noise suppression and echo cancellation engine
KEYBOARD & INPUT	<ul style="list-style-type: none"> 10-point gloved multi touch 2 buttons (user-definable) On-screen QWERTY keyboard
SENSORS	<ul style="list-style-type: none"> Ambient light sensor and acceleration sensors
CAMERAS	<ul style="list-style-type: none"> Full HD 8MP rear camera with LED light
EXPANSION	<ul style="list-style-type: none"> microSDXC (up to 64 GB)²
INTERFACE	<ul style="list-style-type: none"> Docking connector Micro-USB option to be host or client interface 2.0 (x1)³ Mini-jack stereo headphone & microphone xPak interface
WIRELESS	<ul style="list-style-type: none"> Qualcomm® WCN3660B IEEE802.11 a/b/g/n/d/h/i/r Qualcomm® MSM8909 - 4G LTE, HSPA+, UMTS, EDGE, GPRS, GSM Nano SIM card slot (x1) Bluetooth® v4.2 Classic Mode LE (class 1) GPS GPS/GLONASS CEP50 (±2 to 4 m) Near Field Communication (NFC) <ul style="list-style-type: none"> Type A, Type B, Felica
POWER SUPPLY ^{4,5,6,7,8,9,10,11}	<ul style="list-style-type: none"> Standard battery: Li-ion 3.8V, 3,200 mAh Standard battery operation <ul style="list-style-type: none"> 12 hours based on standard enterprise user profile⁹ Warm Swap Standard battery charging time: <ul style="list-style-type: none"> Power on or off approx. 2 hours⁴ Micro-USB charging capability sold separately⁵
POWER MANAGEMENT ¹¹	<ul style="list-style-type: none"> Consumption approx, 13W^{12,13} Warm swap battery
SECURITY FEATURES	<ul style="list-style-type: none"> ARM® TrustZone® (Built-in)
WARRANTY	<ul style="list-style-type: none"> 1-year limited warranty, parts and labor
DIMENSIONS & WEIGHT ^{14,15}	<ul style="list-style-type: none"> 3.0" x 6.1" x 0.5"/0.7" (barcode reader section) Approx. 0.53 lb. with Standard Battery

KEY FEATURES

- 1D/2D barcode reader (SE4710) with LED light

ACCESSORIES

Single Bay Desktop USB I/O and charge cradle with 5v power supply and AC cord	FZ-VEH1T1AAM
5-Bay Desktop Ethernet I/O and charging cradle with 110W power supply and AC cord	FZ-VEH5T1AAM
5-Bay Desktop charge-only cradle with 110W power supply and AC cord	FZ-VCH5T1AAM
5-Bay Battery charger	FZ-VCBT131M
Charging cup with desktop stand (charge only) (No power supply or AC cord)	FZ-VCBT11U
Standard Battery 3,200mAh for FZ-T1	FZ-VZSUT10U
Standard battery 3,200mAh for FZ-T1 - 10 Pack	FZ-VZSUT1AU
USB Charger ⁵	FZ-AAE184EM
Holster	FZ-VSTT12U
Pistol grip	FZ-VGGT111U
Passive Stylus Pen	CF-VNP021U
Tethers -3 Pack	FZ-VNTT11U
Screen protector films - 10 Pack	FZ-VPFT11U

Please consult your reseller or Panasonic representative before purchasing.

Specifications given herein may be changed at any time without prior notice.

¹ 1 MB = 1,048,576 bytes. 1 GB = 1,073,741,824 bytes

² Operation has been tested and confirmed using the following Panasonic brand memory cards: SD (up to 2 GB), SDHC (up to 32 GB), SDXC (up to 64 GB). Compatibility with other SD devices is not guaranteed.

³ Does not guarantee operation of all USB-compatible peripherals.

⁴ (TBD)

⁵ The AC adaptor is designed for use with power sources that supply up to 240 V AC.

⁶ Actual performance varies depending on usage conditions, connected peripherals, etc. Typically, operating time is reduced in colder environments.

⁷ Talk time may vary depending on the condition of the mobile network.

⁸ As defined by the JEITA Specification, Working Mode B. (Two times reading in every 10 seconds)

⁹ Enterprise user profile: Barcode usage of 3 scans per minute; WWAN data transfer usage of 90 seconds every 10 minutes; Wi-Fi usage of 30 minutes; Cellular voice usage of 15 minutes

¹⁰ Charging with optional charging cup or cradle. Varies depending on usage conditions.

¹¹ Need to turn on battery warm swap mode before remove the battery. You can turn on battery warm swap mode by UI operation or FZ-T1 automatically turns into battery warm swap mode when the battery is removed.

¹² When the battery is fully charged (or not being charged) and the unit is off.

¹³ Powered with optional charging cup or cradle. Rated power consumption.

¹⁴ Actual size may vary by unit configuration.

¹⁵ Average weight. Actual weight may vary by unit configuration.

¹⁶ Do not expose the skin to this product when using the product in a hot or cold environment. When using the product in hot or cold environments, some peripherals may not perform properly. Confirm the recommended operation environment of the peripherals. Using the product continuously in hot environments will shorten the product life. Avoid continuous use in these types of environments. When using the product in cold environments, the product may take longer to start up and battery operation time may be reduced. Even when using the product within the temperature and humidity ranges listed here, using the product continuously in extreme environments will result in product deterioration and will shorten the life of the product.

¹⁷ Product functionality cannot be guaranteed if the operating system is modified or replaced by the user or a third party.



1.866.413.3099

business.panasonic.ca

Android, Google, and Google Play are trademarks of Google Inc. Panasonic is constantly enhancing product specifications and accessories. Specifications subject to change without notice. Trademarks are property of their respective owners. ©2018 Panasonic Systems Corporation of North America. All rights reserved. Toughbook FZ-T1 mk1 Spec Sheet 07/18. PSC-M181023SS

TOUGHBOOK®